

### AC POWER & DATA CONNECTIVITY SOLUTION

M-POWER-3TBR2-ABY-BR2ATP(2)

Distributed by



Mormax Company, Inc.

8 Westchester Plaza

Elmsford, NY 10523

914-699-0101 sales@mormax.com


mormax.com


Metro Light & Power's line of power & data solutions offers sophisticated design elements combined with greater ease of installation. Streamlined and low-profile, enhanced by side-exiting cords, our outlets advance the industry with their cutting edge look and feel. We believe flexibility is key, and we provide a variety of mounting options, including the ability to mount in limited spaces. Our outlets are available in many finishes and configurations, in addition to a custom color and finish capability for our clients.

Trim Plate Finish: UNICOLOR™ BRASS (ABS)

Custom Finishes Available

M-POWER-3TBR2-ABY-BR2ATP(2)





#### Features:

### **Module/Port Options:**

- A Tamper Resistant AC Receptacle
- B USB-A & USB-C (3.0A USB-A / 15W USB-C)
- U Double USB-A (Fast Charging Ports Rated for 3.2A)
- H HDMI
- 6 CAT 6
- 12 RJ 12
- X Switched AC
- Y 3-Way Switch (Low Voltage)
- C USB-C (27W High Speed Charging Port)
- Z USB-C (18W High Speed Charging Port)
- R Switched AC (Rocker Switch)
- Dimmer Switch

# Plug:

Supplied with Low Profile Flat 45° Angle 120 VAC Plug

Optional Standard Straight 120 VAC Plug

Optional Straight 120 VAC Pass-through Plug

- CLEAN, COMPACT DESIGN
- STREAMLINED
- LOW PROFILE
- SIDE-EXITING CORDS
- PLUG & PLAY
- 6' AC CORD & PLUG (FLAT PLUG STANDARD)
- CUSTOMIZABLE CONFIGURATIONS AND FINISHES
- UL LISTED FOR MOUNTING IN FURNITURE
- 15A

 $\wedge$ 

UL LISTED AND APPROVED FOR USE ONLY WITH METRO LIGHT & POWER'S UL LISTED LEDS & CLASS 2 UL LISTED LED DRIVERS





### AC POWER & DATA CONNECTIVITY SOLUTION

M-POWER-3TBR2-ABY-BR2ATP(2)

## Distributed by



Mormax Company, Inc.
8 Westchester Plaza

Elmsford, NY 10523

 $\mathcal{C}$ 

914-699-0101

 $\overline{\square}$ 

sales@mormax.com mormax.com

### **Modules/Ports:**

- A Tamper Resistant AC Receptacle
- **B** USB-A & USB-C (3.2A USB-A / 15W USB-C)
- Y 3-Way Switch

